

# FAQ

## Flashing

Question	Answer
“Error, Flash download failed - Could not load file './.axf”	Project not compiled, go to 'Project → Build Target (or press F7). Errors in code may be causing compilation to fail. Check that the number of errors is zero when compiling.
“No target connected”	Quad not powered on, you need to supply power to the board; either plug the battery, or the serial cable. If powered, check your clk and data connections. This message indicates the computer can't communicate to the quadcopter.
“Unknown target connected”	Wrong chip selected, go to “Project → Options For Target (Alt + F7)”. New window opens, switch to 'Debug' tab and on top right, press “ST-Link Debugger” Settings button. New window opens, switch to 'Flash Download' tab, select the proper chip family, press Remove, then Add, and then select the proper chip.
Internal Command Error. Error: Flash Erase failed - Target DLL has been cancelled“	Your programming wires might be too long. Try to keep them as short as possible.
ST-link USB communication error or similar popup	Disconnect/reconnect st-link from USB. This may also be a special blue board problem. read <a href="#">here</a>
Select device menu grayed out	This is from video, use text instructions from post, or skip the related steps

From: <https://sirdomsen.diskstation.me/dokuwiki/> - **Silverware Wiki**

Permanent link: <https://sirdomsen.diskstation.me/dokuwiki/doku.php?id=faq&rev=1516104209>

Last update: **2018/01/16 13:03**

